

## Sensormatic® PowerPad® Pro Ultra•Max® Label Deactivator



### Description

The PowerPad Pro is a ScanMax™ distance deactivator providing superb deactivation reliability, impressive throughput speed, and an optional magnetic media safe mode to safeguard pre-recorded video and audio cassettes.

The PowerPad Pro can be mounted in a variety of ways including on the counter, below counter, flush with the counter or on a bracket at the edge of the counter.

PowerPad Pro deactivates labels up to 17.5 cm (7 in.) above the surface of the pad at a throughput speed of up to 200 cm/sec. (80 in./sec.).

### Features

- **Performance.** The PowerPad Pro's deactivation height allows deactivation of both source tagged and retailer tagged merchandise.
- **Magnetic media safe.** A magnetic media safe mode at reduced height safeguards pre-recorded audio and videocassettes.
- **Integrated audible and visual notification.** Label deactivation notification is built into the PowerPad Pro. A remote module with a key switch also can provide visual and audible confirmation of label deactivation.

### Specifications

#### Power

100-120 / 200-240 Vac; 1A @ 50-60Hz

#### Power Consumption

Typical: 10W @ 120V, 15W @ 240V

Max: 50W @ 120V and 240V

#### Operating Frequency

58 kHz ( $\pm 200$  Hz)

#### Operating Temperature

0° to 40° C (32° - 104° F)

#### PowerPad Dimensions

LxWxD: 39.4 x 17 x 5.6 cm  
(15.5 x 6.75 x 2.2 in.)

Weight: 9.6 kg (21 lbs.)

Cable: 2.9 m (9.7 ft.)

#### Controller Dimensions

HxWxD: 10.1 x 26.2 x 22 cm  
(4.0 x 10.3 x 8.7 in.)

Weight: 2.5 kg (5.5 lbs.)

#### Controller Emissions

47 CFR, Part 15

ENS 300 330

EN 301489

EN61000-3-2

EN61000-3-3

#### Controller Safety

UL60950

CSA C22.2 No. 60 950

EN 60 950

**tyco**  
Safety  
Products

# ELECTRONIC ARTICLE SURVEILLANCE



The PowerPad Pro is available as a table top, under-the-counter or end-of-the-counter deactivator.



The compact ScanMax Pro Controller features table-top, vertical, and under-the-counter mounting options.

## Remote module




The remote module can be mounted almost anywhere on the checkstand for visual and audible notification of deactivation. The module features a key switch for turning the deactivator on or off.

The PowerPad Pro will deactivate Ultra•Strip® II and Ultra•Strip III labels. Place labels within 8.9 cm (3.5 in.) of the bar code for optimal deactivation performance and convenience.



Ultra•Strip III



Ultra•Strip II

## ScanMax Pro Controller


The ScanMax Pro Controller provides the power and operating capabilities to the deactivator antenna. It is compatible with all ScanMax Pro deactivator antennas. Its features include:

- Deactivates up to two labels per second.
- Small size requires minimal space.
- Optional mounting bracket for under-the-counter or sidewall installation.
- Automatically detects antenna type and remote module.
- Simple button press to select deactivation mode and label type.
- Auto phasing capability.
- Separate communications ports for POS and service.

For further details on all ScanMax Pro products, refer to the ScanMax Pro Deactivator Systems Planning Guide 8200-0054-02.

## Deactivator mounting options

Flush mount, end-of-the-counter flip-down tray, and under-the-counter mounting.



End-of-counter brackets

## Product Codes

- ZBSMP-PW..... System, including deactivator, controller, remote alarm module, power cord
- ZESMPRO ..... Controller with cord
- ZBSMPRO ..... Controller only
- ZBSMPPP ..... Deactivator only
- ZBSTP-PP-B1 ... Flush mount tray
- ZBSTP-PP-B2 ... Under-the-counter bracket
- ZBSTP-PP-B3 ... Cantilever mounting bracket
- ZBSTP-PP-B4 ... Flip Mount bracket

**tyco**

Safety  
Products